

TEDMON

This is a very short description of the built in machine language monitor "Tedmon" on the Plus/4 and C16. You start the monitor with the MONITOR command from basic. These are the available commands in Tedmon:

Assemble

A <address> <opcode> <operand>

A 2000 LDA#\$00

(A period (.) is equal to A)

Compare

C <start address> <end address> <compare start address>

C 2000 2008 4000

Disassemble

D [<start address>] [<end address>]

D 2000

D

Fill

F <start address> <end address> <byte>

F 2000 2800 00

Go

G <address>

G 2000

(equal to SYS 8192 from basic)

Hunt

H <start address> <end address> <data>

H 2000 3000 FF

H 1000 103F 4E F8

H 0000 2000 'STRING

Load

L <"file name"> [<device>]

L "program" 08

Memory

M [<start address>] [<end address>]

M 2000

M

(> to edit memory)

Registers

R

(; can be used to modify registers)

Save

S <"file name"> <device> <start address> <end address>

S "program" 08 2000 21F4

Transfer

T <start address> <end address> <to address>

T 2000 20E0 3000

Verify

V <"file name"> [<device>]

V "program" 08

Exit

X